



MAGNETIC BALLASTS FOR FLUORESCENT LAMPS: FB-13



Power (W)	Voltage (V)	Frequency (Hz)	Power factor	weight (kg)	current at 230 V (A)
13	220-240	50	0,52	0,4	0,165
2*7	220-240	50	0,47	0,4	0,175
2*9	220-240	50	0,55	0,4	0,165

Technical characteristics:

- ❖ Magnetic ballast for flat or narrow lamps
- ❖ Resin impregnation and heating
- ❖ Protection class I
- ❖ Compensation with capacitors $2 \mu\text{F} \pm 10\%$
- ❖ Dielectric stiffness : $> 1500 \text{ V}$
- ❖ Screw terminals : $0,75\text{-}2,5 \text{ mm}^2$
- ❖ Safety Standards : NF EN-61 347 & NF EN- 60 921

Wiring diagram :

