




## MAGNETIC BALLASTS FOR FLUORESCENT LAMPS: FB-18



Power (W)	Voltage (V)	Frequency (Hz)	Power factor	weight (kg)	current at 230 V (A)
18	220-240	50	0,5	0,32	0.22

### Technical characteristics:

- ❖ Magnetic ballast for flat or narrow lamps
- ❖ Resin impregnation and oven drying
- ❖ Protection class I
- ❖ Compensation with capacitor 4  $\mu$ F  $\pm$ 10%
- ❖ Dielectric stiffness : > 1500 V
- ❖ Screw terminals : 0,75-2,5 mm<sup>2</sup>
- ❖ Safety Standards : NF EN-61 347 & NF EN- 60 921

### Wiring diagram :

